

: means press down(ON) : means up position(OFF)

Thanks for buying LED Light product series, the manual of LED dip switch is convenient for you very much. Strong suggestion for End-user PLEASE READ instruction before operate; The device has been passed high QC-and-well tested before delivery to ensure the best performance. Please DO FOLLOW the instruction steps to prevent the possible malfunction.(including Remote Control item)


1. DMX-512 controllable :

you can use DMX controller to edit LED products,just use your finger to show every possible effects on your own

4 channels : RED, GREEN, BLUE, (Dimmer&Flash)


*** Synchronisation method 1:**

when use DMX controller, **Master&Slave** dip switch are set all 1 "ON"



Note: when synchronisation, one of them disconnected or non-synchronisation==> please move channel (Dimmer&Flash) up and down can solve this phenomenon

*** Synchronisation method 2:**



First Unit : dip switch 1 set "ON"

Second Unit: dip switch 1 and 3 set "ON"

Third Unit: dip switch 1 and 4 set "ON"

• • • • • etc.


Due to 4 channels, plus 4 each time to set next Unit, then use DMX controller to edit Synchronisation steps.

Note: Use connector to connect the DMX signal in this unit, use out connector to link DMX signal with next unit

2. Built-in 8 Effects Dip Switch operate explanation:


please print out the forward page "LED DIP SWITCH TABLE" for your reference

***1. 00: Sound effect**




1~12 are all set "OFF"

***2. A1: Auto off when there is no sound in 10 secs**



10 set "ON" the others set "OFF"

***3. A2: Fade in fade out with 12 color changing rate via DIP switch**



11 set "ON" the others set "off"

☆Color changing time adjustable

- 5 set "ON" : color change in 2 secs
- 6 set "ON" : color change in 3-4 secs
- 7 set "ON" : color change in 5-7 secs
- 8 set "ON" : slowest color change in 8-10 secs
- 5,6,7,8 are all set "OFF" : fastest color change

Note1: **A3(strobe effect) & A4(Flash effect)** are also color change time adjustable, using the same way to adjust the effects

Note2: **A5(Strobe on sound effect) & A6(Auto-change colors in 3 secs non-sound input)** are using A1 concept to adjust the light effect


***4. A7 : 7 selectable individual colors**

first step : 10, 11 and 12 are set "ON"

second step : 1 set "ON", the light turn "RED" color; 1 set "OFF" --> 2 set "ON", the light turn "WHITE"; 2 set "OFF" --> 3 set "ON", the light turn "YELLOW" color; same concept to control single color you desired!

Safety precaution

***1. Light-safety information**



***2.**

- *Appliance shall only be used with rated voltage and frequency
- *Don't move the appliance with aid of supply cord
- *if the appliance is not used, please turn off
- *Don't use or stop working if the appliance is damaged, especially the supply cord or the case
- *Children don't recognise the risks of electrical appliances. Therefore use or keep the appliance only under supervision of adults and out of the reach from children
- *Laser related warnings acc to Laser class 2

ODYSSEY LED DIP SWITCH TABLE

LED DIP SWITCH Guide:

■ : means press down

□ : means up position

	A7				A6				A5				A4				A3				A2				A1				00			
	1	2	3	4	1	2	3	4	1	2	3	4	1	2	3	4	1	2	3	4	1	2	3	4	1	2	3	4	1	2	3	4
5	□	□	□	□	□	□	□	□	□	□	□	□	☆	☆	☆	☆	☆	☆	☆	☆	☆	☆	☆	☆	□	□	□	□	□	□	□	□
6	□	□	□	□	□	□	□	□	□	□	□	□	☆	☆	☆	☆	☆	☆	☆	☆	☆	☆	☆	☆	□	□	□	□	□	□	□	□
7	□	□	□	□	□	□	□	□	□	□	□	□	☆	☆	☆	☆	☆	☆	☆	☆	☆	☆	☆	☆	□	□	□	□	□	□	□	□
8	□	□	□	□	□	□	□	□	□	□	□	□	☆	☆	☆	☆	☆	☆	☆	☆	☆	☆	☆	☆	□	□	□	□	□	□	□	□
9	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□
10	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	■	■	■	■	■	■	■	■	■	■	■	■	□	□	□	□
11	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	■	■	■	■	■	■	■	■	□	□	□	□	□	□	□	□
12	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□	□

Sound effect

Auto off when there is no sound in 10 secs

Fade in fade out

Strobe

Flash

Strobe on sound effect

Auto-change-colours in 3 secs non-sound input

Stand individual colour set up provide 7 colors choice, pick out one of 1-8 each time

***color change time only suits for: light in light out/ Strobe/Flash

☆	indigo	☆	blue	☆	purple	☆	
0	0	0	0	0	0	0	0
0/1	0/1	0/1	0/1	0/1	0/1	0/1	0/1
0	0	0	0	0	0	0	0

fastest

color change in 2 secs

color change in 3-4 secs

color change in 5-7 secs

slowest color change in 8-10 secs

